

Electronics

Compact and Cost Effective Dual Stage RFI Power Line Filters

EMC Series



UL Recognized CSA Certified VDE Approved





EMC6


EMC1

EMC Series

The EMC Series of RFI filters has been developed to reduce conducted noise to acceptable limits for equipment that must comply with the requirements of CISPR in Europe and the FCC specifications in the USA.

The EMC Series is the most compact dual stage filter available from Tyco Electronics. This cost effective design has a maximum current rating of 30 amps; higher than any similar catalog product. The EMC Series was designed to address the need for more differential mode attenuation in the lower frequency range while still maintaining high common mode performance. This type of performance is typically needed for motor drives and switch mode power supplies with increased operating frequencies. The EMC Series is ideal for applications that require a high level of performance in a compact, cost effective package.

Electrical Schematic



Resistor location for reference only.

Specifications

Maximum leakage current, each line-to-ground

| , | 3,6,10 Amp | 15,20,30 Amp |
|--|------------|----------------------|
| @ 120 VAC 60 Hz: | .21 mA | .73 mA |
| @ 250 VAC 50 Hz: | .43 mA | 1.52 mA |
| Hipot rating (one minute): line-to-ground line-to-line | | 2250 VDC 1450 VDC |
| Operating frequency: | | 50/60 Hz |
| Rated voltage (max.): | | 250 VAC |

Minimum insertion loss in dB:

Line-to-ground in 50 ohm circuit

| Current | Frequency-MHz | | | | | | | | | |
|---------|---------------|-----|-----|-----|----|----|----|----|----|--|
| Rating | .05 | .07 | .11 | .15 | 1 | 2 | 10 | 20 | 30 | |
| 3A | 6 | 6 | 3 | 16 | 65 | 66 | 62 | 60 | 59 | |
| 6A | 6 | 6 | 2 | 15 | 65 | 67 | 65 | 62 | 63 | |
| 10A | 5 | 2 | 13 | 24 | 72 | 72 | 56 | 50 | 48 | |
| 15A | 3 | 1 | 12 | 22 | 70 | 68 | 57 | 54 | 53 | |
| 20A | 2 | 2 | 11 | 21 | 58 | 57 | 63 | 55 | 52 | |
| 30A | 2 | 2 | 14 | 22 | 47 | 52 | 60 | 48 | 43 | |

Line-to-line in 50 ohm circuit

| Current | | | Fr | equer | ncy-M | Hz | | | | |
|---------|-----|-----|-----|-------|-------|----|----|----|----|--|
| Rating | .05 | .07 | .11 | .15 | 1 | 2 | 10 | 20 | 30 | |
| 3A | 12 | 13 | 7 | 18 | 64 | 69 | 65 | 60 | 52 | |
| 6A | 12 | 12 | 8 | 27 | 61 | 61 | 59 | 56 | 54 | |
| 10A | 14 | 15 | 12 | 33 | 54 | 58 | 47 | 34 | 36 | |
| 15A | 16 | 16 | 13 | 34 | 61 | 52 | 36 | 36 | 23 | |
| 20A | 17 | 19 | 15 | 37 | 67 | 62 | 36 | 32 | 30 | |
| 30A | 17 | 18 | 14 | 40 | 62 | 53 | 30 | 28 | 26 | |

49-89-6089-0

Germany:

RFI Power Line Filters


Electronics

Compact and Cost Effective Dual Stage RFI Power Line Filters (Continued)

EMC Series

Case Styles

EMC₁




Terminals: .250 [6.35]

Mounting Holes: .187±.008 [4.75±.20] Dia.(2)


Mounting Holes: .187±.008 [4.75±.20] Dia.(2)

EMC3




Wire leads: 4.0 [101.6] min. 3,6,10A:18 AWG / 15A: 16 AWG Mounting Holes: .187±.008 [4.75±.20] Dia.(2)

EMC6



30EMC6

Terminals: 8-32 (5)



Case Dimensions

| Part No. | A (max) | B (max) | C (max) | D (max) | E (max) |
|----------|------------|------------|------------|------------|------------|
| | 3.35 | 1.81 | 1.16 | 2.375 | 2.78 |
| 3EMC1 | 85.1 | 46.0 | 29.5 | 60.3 | 70.6 |
| 6EMC1 | 3.85 | 2.07 | 1.16 | 2.938 | 3.35 |
| OLIVIOT | 97.8 | 52.6 | 29.5 | 74.6 | 85.1 |
| 4051404 | 3.85 | 2.07 | 1.53 | 2.938 | 3.35 |
| 10EMC1 | 97.8 | 52.6 | 38.91 | 74.6 | 85.1 |
| 15EMC1 | 4.97 | 2.25 | 1.78 | 4.063 | 4.46 |
| 20EMC1 | 126.2 | 57.2 | 45.2 | 103.2 | 113.3 |
| 3EMC3 | 2.07 | 1.81 | 1.16 | 2.375 | 2.78 |
| 3LIVIO3 | 52.6 | 46.0 | 29.5 | 60.3 | 70.6 |
| 6EMC3 | 2.56 | 2.07 | 1.16 | 2.938 | 3.35 |
| | 65.0 | 52.6 | 29.5 | 74.6 | 85.1 |
| 10EMC3 | 2.56 | 2.07 | 1.53 | 2.938 | 3.35 |
| TOLIVIOO | 65.0 | 52.6 | 38.9 | 74.6 | 85.1 |
| 15EMC3 | 3.69 | 2.25 | 1.78 | 4.063 | 4.47 |
| TOLIVIOS | 93.7 | 57.2 | 45.2 | 103.2 | 113.5 |
| 10EMC6 | 3.94 | 2.07 | 1.53 | 2.938 | 3.35 |
| TOLIVICO | 99.9 | 52.6 | 38.9 | 74.6 | 85.1 |
| 15EMC6 | 5.09 | 2.25 | 1.78 | 4.063 | 4.47 |
| 20EMC6 | 129.3 | 57.2 | 45.2 | 103.2 | 113.5 |
| 30EMC6 | 6.05 | 3.12 | 2.18 | 3.50 | 3.96 |
| SOLIVIOU | 153.7 | 79.2 | 55.4 | 88.9 | 100.6 |

Part Numbers

| 3EMC1 6EMC1 10EMC1 | 10EMC3 15EMC3 10EMC6 |
|--------------------------|----------------------------|
| 15EMC1 | 15EMC6 |
| 20EMC1 | 20EMC6 |
| 3EMC3 | 30EMC6 |
| 6EMC3 | |